

SPECIFICATIONS

Output: 5ft = 40fc, 2.5ft = 160fc
Color Temperature: 3000 – 5600K
CRI ≥92
Run Time: 1 Hour 40 Minutes
LED Count: 120 Elements
Power Consumption: 8W
Battery capacity: 2700mAh
Weight: 5.2 ounces
Dims: L 3.34" x W 2.24" x .39" Thick
Mount: Cold Shoe
Charge Method: USB



Instructions

Pocket Light LED Kit Smart Phone Pocket Light Kit*

Accessories and Ordering Information

Pocket Light LED Kit	Smart Phone Pocket Light Kit
 LED Light	 LED Light
 Pouch	 Phone Mount
 Shoe Mount	 Tripod/ Handle
 USB Charge Cable	 Pouch
	 USB Charge Cable
	 Shoe Mount
Model LCL-120 Item No. 91731	Model LCL-120K Item No. 91075



Questions?
Call Tech Support (973) 427-1160
8-5pm EST M-F
email support@frezzi.com



www.frezzi.com

PocketLight Manual R1

5 VALLEY STREET
HAWTHORNE, NJ 07506 USA
[HTTP://WWW.FREZZI.COM](http://WWW.FREZZI.COM)
E-MAIL: INFO@FREZZI.COM
PHONE: (973) 427-1160
FAX: (973) 427-0934

READ MANUAL PRIOR TO USE FOR SAFETY WARNINGS
***Smart Phone Pocket Light Kit**

Pocket Light Operation

POWER



PRESS & HOLD Power Button **2 Seconds**. Display will come on

TURN ON LEDS

Short press to turn on LED output.

TURN OFF LEDS

Short press to turn off LED. Instantaneously turn back on, short press again.

TURN OFF UNIT

PRESS & HOLD 2 Seconds.



SET MODE

PRESS to select mode to COLOR or DIMMER




ADJUST

PRESS to adjust COLOR or DIMMER



POWER

DISPLAY



Battery Level

Dimmer Level 85%

Color Temperature 3600K

Mode Indicator (Dimmer/Color Mode)

CHARGING

Charge with supplied USB charge cable. Fully Charged when indicator shows 4 Bars Turn OFF unit while charging.



Mounting and Operation

Mounting to a Camera with Shoe




Screw SHOE MOUNT into bottom of Pocket Light. **Do Not Over Tighten** TIGHTEN Locking wheel to secure to Pocket Light body

Loosen for TILT ADJUSTMENT

Slide SHOE into CAMERA and TIGHTEN locking wheel to secure.

Smart Phone Kit Mounting & Operation




Mount Pocket Light to Phone Holder If using phone in "Selfie" style for a Skype interview, mount light the other way.

Mount phone by pulling open Phone Holder

Mount phone older to Tripod

Pull open Tripod Legs



Phone Holder opens to secure phone

Pull back rear leg



Rotate Light if shooting Selfie Style

Close Tripod Legs to use as Handgrip